



Part of Consilium Safety

Manual Call Point FD3050



The Manual Call Point FD3050 is designed to release a signal for a fire condition to the Fire Control Panel upon manual activation by breaking the glass on the place signed with arrows. The light indication for activating the manual call point is provided by a red LED. It can be tested by a special key without operating the break glass.

It satisfies the requirements of the European Standard EN54-11 for an indoor use manual call point.

Certification:



Technical Features

Electrical Installation	through terminal for connecting wires with cross-section (0.5) - 1.5) mm ²
Supply Voltage	(10-30)V DC
Degree of Protection	IP40 (not verified by UL)
Operational Temperature Range	minus 10°C - plus 55°C
Relative Humidity Resistance	(93±3)% at 40°C
Dimensions, Base Included	98 mm x 96mm x 51mm
Casing Material	ABS red
Weight, Base Included	0.150 kg