

# Addressable Modular System Panel 7000-1MC

The **Addressable Modular System Panel 7000-1MC** features:



Part Number: 7000-1MC

- Compact metal cabinet construction with multiple cable entries
- Simplified and extended keypad for operation
- Supplied with 1 loop as standard
- In-panel ModBus connectivity
- Supports Conventional Zone Modules
- Printer accessory available
- Certified to EN54-2 / 4 / 13

Certification:



## Panel

Dimensions	W 350 x H 350 x D 145 mm
Weight (W/O batteries)	7Kg
Standby battery Size	12V 12Ah ( Quantity 2 off)
Maximum Number of Addressable Devices per Loop	150
Maximum Number of Addressable Devices per Panel	150
Number of Loop Modules per Panel	1 module fitted as standard (Each Loop Module supports one loop)
Number of BIO Modules	up to 3 per panel
Maximum number of devices in a Detection Zone	32 devices (detectors, fire inputs or/and manual call points)
Number of conventional modules (DIN8CL)	up to 5 per panel (Each module supports 8 zones)
Maximum number of Conventional Zones	40
Maximum number of Detection Zones per Loop	32
Maximum number of Alarm Zones per Loop	32
Configurable Week Schedule (Day / Night Mode)	Sensitivity and logic change to detectors, delays change in alarm zones
Maximum number of Protection Zones per Loop	32
Maximum Number of Addressable and Conventional Fire Alarm Devices	up to 35 per loop - conventional and addressable devices (sounders)
Dependencies on more than one alarm signal	<b>CI Mode A</b> (detecting fire by double zone activation) <b>CI Mode B</b> (detecting fire by two zones activation) <b>CI Mode C</b> (detecting fire with inspection time)
Alarm Counter	up to 9,999
Event Log (archive)	10,000 events
Configurable Output to Fire Protection Equipment (addressable output device)	LED indication for activation input for the reception of a confirmatory signal from fire protection equipment, indicated by means of separate indicator
Maximum number of Repeaters	3
Input supply	110-240V ac 50/60Hz.

Temperature rating	-5 to +40C
Humidity	93% RH (non-condensing)
Other Features	<p>alarm zones and protection zones can be activated from any detection Zones (one detection zone cannot activate two alarm zones)</p> <p>configurable sounder melodies in alarm and pre-alarm state (Warning-state) for every Alarm zone.</p> <p>Alarm confirmation input from fire alarm routing equipment</p> <p>Fault monitoring fire protection equipment (in/out)</p> <p>Delay to outputs, day / night mode</p> <p>Fault signals from points</p> <p>Output to fault warning routing equipment</p> <p>Disablement of addressable points</p>